

ANNUNCIATOR MODEL 503A

 **Super Nurse Call**
www.supernursecall.com
888-568-0008



FEATURES:

- Simple, Highly Visual Display
 - One Touch Zone Control
 - Micro-Controller Based
- Fully Programmable with Free Software
- Monitor Closed, Open and Multi-State Circuits (High Security)
 - Input to Output Mapping (Multiple Outputs per Zone)
- Network multiple Annunciators via Communication Module
- Up to 64 Zones with custom options

SPECIFICATIONS

MOUNTING	Surface
SIZE	13" x 13" x 4"
COLOR	Off-White Powder Coated Steel Box with Stainless Steel Faceplate
POWER	Includes 12 VDC Power Supply Requires 110 VAC Input
INPUTS	Normally Closed, Normally Open or High Security Multi-State End-of-Line Resistor Loop (Color Coded)
OUTPUTS	One Open Collector Output per Zone Rated at 24 VDC, 100 mA (Color Coded)
OTHER	Four Auxiliary Control Inputs and 2 Common Zone Outputs may be programmed for a variety of functions



Hotel and Apartment
Doors, Motion Sensors, Gates



Nurse Call
Panic Buttons, Fall Sensors, Cameras



Detention and Social Service
Doors, Motion, Panic Buttons



Perimeter
Vibration Sensors, Motion Sensors

Accessories from Flair:

- Magnetic Contacts
- Fence Vibration Sensors
 - Water Sensors
 - Pagers · Dialers
- Remote Graphic Displays

OPERATION:

Simple, Visual, Intuitive

Flair Multi-Zone Annunciators can be used as "stand alone" annunciators or network with other annunciators via communication module. Graphic Displays are also available. Each zone has a green LED for status, a red LED for alarm, a yellow LED for shunt and a zone control button for acknowledge, reset and bypass functions. Zone and common input and output type, timers and other features are programmable with easy to use free software.